



Name	Value
X2	FR-30
1	GND
2	LCD_R3
3	LCD_R4
4	LCD_R5
5	LCD_R6
6	LCD_R7
7	GND
8	LCD_G2
9	LCD_G3
10	LCD_G4
11	LCD_G5
12	LCD_G6
13	LCD_G7
14	GND
15	LCD_B3
16	LCD_B4
17	LCD_B5
18	LCD_B6
19	LCD_B7
20	GND
21	LCD_CLK
22	LCD_VS
23	LCD_HS
24	LCD_DE
25	GND
26	XP
27	XM
28	YP
29	YM
30	3.3V

MiniPCIe		mPcle.edge	
1	GND	2	5V
3	USB0_DM	4	5V
5	USB0_DP	6	5V
7	USB0_DET	8	5V
9	USB0_VBUS	10	Battery
11	USB1_DM	12	RESET
13	USB1_DP	14	GND
15	USB1_VBUS_DET	16	PB13
17	GND	18	PB14
19	CAN_RX	20	PB15
21	CAN_TX	22	PB12
23	UART_TX_Console	24	PG14
25	UART_RX_Console	26	PG13
27	I2C1_SDA	28	PG10
29	I2C1_SCL	30	PG11
31	3.3V	32	PG12
33	SD_D1	34	PG15
35	SD_D0	36	PG16
37	SD_CLK	38	PG19
39	SD_CMD	40	PG18
41	SD_D3	42	PG12
43	SD_D2	44	PG13
45	ETH_CT	46	PB2
47	ETH_TXP	48	PB3
49	ETH_TXN	50	XM
51	ETH_RXP	52	GND

SK-NUC906-NANO
www.starterkit.ru
www.out4.ru

V1A